


How to Use XML Browser on Htek IP Phones



Note:

About XML Browser, HANLONG IP Phone supports TextMenu, TextScreen, Directory, Status, Execute, FormattedTextScreen , InputScreen , ImageScreen and Configuration . If you have any questions when test this part, please feed back to us.

Fistly, build a HTTP server.

For example:

HTTP Server,Port:8080

Host address:192.168.0.240

Before you test ,you need to modify the URL in the TextMenu.xml(e.g:


`<UR>http://192.168.0.240:8080/xmlbrowser/Directory.xml</UR I>`) .

and in the ImageScreen.xml(`<Image horizontalAlign="middle"`

`verticalAlign="bottom" >http://192.168.0.240:8080/xmlbrowser/3.bmp</Image>`)

Test steps:


Step 1: Put the .xml files into upgrade directory: E:/xmlbrowser



Step 2: Login the IP Phone's webpage: Function Keys->Line key, select the Type :XML Browser;Value:<http://192.168.0.240:8080/xmlbrowser/TextMenu.xml>->Click "SaveSet" button:

| Line Key | Type | Value | Label | Account | Pickup Code |
|----------|-------------|------------|-------|---------|-------------|
| Key1 | Line | | | Auto | |
| Key2 | Line | | | Auto | |
| Key3 | Line | | | Auto | |
| Key4 | XML Browser | http://192 | | Auto | |

Step 3: Hitting the Line key 4 on the Phone, you can see the following content:





Step 4: Choosing the TextScreen column by hitting up/down arrow, then hitting the Select button.



Step 5: Hitting the Exit button to return to the previous interface.

Step 6: Choosing the Directory column by hitting up/down arrow, then hitting the Select button.




Hitting the Next button can choose the contact.

Hitting the Previous button can choose the previous contact.

Hitting the Dial can dial out.

Step 7: Hitting the Exit button can return to the previous interface

Step 8: Choosing the Status column by hitting up/down arrow, then hitting the Select button.




Step 9: Hitting the Line key 4 to enter the TextMenu interface


Step 10: Choosing the Execute column by hitting up/down arrow, then hitting the Select

button, then the Phone will execute the command `<ExecuteItem`

`URI="Led:LINE1=fastflash"/>` in the Execute.xml





Step 11: Choosing the FormattedTextScreen column by hitting up/down arrow, then hitting the Select button:






Step 12: Choosing the ImageScreen column by hitting up/down arrow, then hitting the Select button, the image (support the .jpg/.png/.bmp) will show on the LCD:





Step 13: Choosing the InputScreen column by hitting up/down arrow, then hitting the Select button:




The InputScreen.xml:

```
<?xml version="1.0" encoding="ISO-8859-1"?>
<InputScreen
  type="string"
  Beep="yes"
  Password="no"
  Timeout="0"
  LockIn="no"
  inputLanguage="English"
  displayMode = "normal"
```




```
defaultIndex="2" >
<Title wrap="yes">Input Info</Title>
<URL>http://192.168.0.240:8080/xmlbrowser/Directory.xml</URL>
<InputField type="number" password="no" editable="no">
  <Prompt>User ID:</Prompt>
  <Parameter>userid</Parameter>
  <Selection>1QQQQ</Selection>
  <Default>21501</Default>
</InputField>
<InputField type="IP" password="no" editable="yes">
  <Prompt>IP Address:</Prompt>
  <Parameter>IP</Parameter>
  <Selection>2</Selection>
  <Default>192.168.0.138</Default>
</InputField>
<InputField type="string" password="no" editable="yes">
  <Prompt>Name:</Prompt>
  <Parameter>user</Parameter>
  <Selection>5QQQQ</Selection>
  <Default>jxz</Default>
</InputField>
<InputField type="string" password="yes" editable="no">
  <Prompt>password:</Prompt>
  <Parameter>passwd</Parameter>
  <Selection>4</Selection>
  <Default>123456</Default>
</InputField>
</InputScreen>
```

Then you can see the content input on the Screen:



You can edit the IP Address, Name, password information.

Step 14: Choosing the Configuration column by hitting up/down arrow, then hitting the Select button:



The Configuration.xml:

```
<?xml version="1.0" encoding="ISO-8859-1"?>
<PhoneConfiguration
  Beep="yes" >
  <P271 para="Account1.Active">1</P271>
  <P47 para="Account1.Sipserver">192.168.0.9</P47>
  <P20000 para="Account1.Lable">500</P20000>
  <P35 para="Account1.SipUserId">500</P35>
  <P36 para="Account1.AuthenticateID">500</P36>
```


```
<P34 para="Account1.AuthenticatePassword">test11</P34>
<P3 para="Account1.DispalyName">500</P3>
<!--
<P41203 para="LineKey4.Type">3</P41203>
<P41303 para="LineKey4.Value"></P41303>
<P41403 para="LineKey4.Label"></P41403>
<P41503 para="LineKey4.Account"></P41503>
<P41603 para="LineKey4.PickupCode"></P41603>
<P42200 para="MemoryKey1.Type">5</P42200>
<P42300 para="MemoryKey1.Value"></P42300>
<P42400 para="MemoryKey1.Account"></P42400>
<P42500 para="MemoryKey1.PickupCode"></P42500>
-->
```

</PhoneConfiguration>

Then you can see the Line 1 is registered:




Step 15: Choosing the ImageMenu column by hitting up/down arrow, then hitting the Select button:



The ImageMenu.xml:

```
<?xml version="1.0" encoding="ISO-8859-1"?>
<ImageMenu Beep="yes" Timeout="120" mode="regular">
<Image verticalAlign="top"
horizontalAlign="left">http://192.168.0.240:8080/xmlbrowser/ImageMenu.jpg</Image>
<URIList base="http://192.168.0.240:8080/xmlbrowser/">
<URI key="#">http://192.168.0.240:8080/xmlbrowser/TextMenu.xml</URI>
<URI key="0">Directory.xml</URI>
<URI key="1">http://192.168.0.240:8080/xmlbrowser/InputScreen.xml</URI>
</URIList>
</ImageMenu>
```



Press # ,then enter the TextMenu column

Press **0** ,then enter the Directory

Press **1** ,then enter the InputScreen

You can custom the <URI key="**custom**"> you want.